


Amplificadores de sistema

MA-2.1200

Amplificador de sistema para instalaciones fijas, 2 × 1200 W, 1 U, 19".



Analog

AES/EBU

AIREA®

Dante™

Amplificadores de sistema MA-2.1200

El MA-2.1200 es un amplificador digital compacto de 2 canales con una matriz de enrutamiento de 4×2 . Forma un componente potente y fiable en su instalación fija y es extremadamente flexible y rentable. La integración en controles de medios y redes de audio es posible sin dificultad y la configuración también se puede realizar muy fácilmente a través de una toma USB-C con Fohhn Audio Soft.



Main features

- Potencia de salida: $2 \times 1200 \text{ W}$ / 4 ohmios / 100 V / 70 V
- Disponible en dos variantes: Con entradas analógicas (MA-2.1200 ANA) o Dante Entrada (MA-2.1200 DAN)
- Compacto y ligero: 1 U, 5,2 kg
- Soportes de montaje para rack incluidos
- Dos contactos de conmutación libremente programables
- Con la conexión Fohhn Airea
- Puede manejarse y controlarse a distancia a través de Fohhn Net
- Q-SYS Plugin disponible en combinación con Fohhn NA-4 o ABX-6
- Ventilador de temperatura controlada y bajo nivel de ruido
- Auto Power Save para las necesidades mínimas de energía de reserva
- Los preajustes de los altavoces Fohhn garantizan la máxima seguridad, fiabilidad y excelente calidad de sonido



Disponible con las siguientes opciones de color



Negro

Equipado con las siguientes tecnologías Fohhn



Fohhn Airea



Fohhn DSP
dentro de

100 V

100 V opcional



Auto Power
Save



Power Sharing

Posibles interfaces de entrada para este producto

Analog

AES/EBU

AIREA

 **Dante**

Datos técnicos

Physical features	
dimensions (w × h × d)	1 U / 19", 440 × 45 × 370 mm
weight	5.2 kg
Electronic features	
amplifier technology	Class D
amplifier outputs	2
DSP routing (matrix)	4 × 2
frequency response	20 Hz – 20 kHz
signal/noise ratio	> 103 dB/A
THD+N	0,15 % (1 kHz, 8 ohms, 3 dB below clipping)
dynamic range	> 120 dB
password protection	yes
auto power save	adjustable from 1 s to 12 h, or never active
protective circuit	over voltage protection, over current protection, over temperature protection, short-circuit protection, DC protection, power on delay, soft start and inrush current limit
power supply	100 – 240 V AC 50/60 Hz, universal power supply with Power Factor Correction (PFC)
power consumption	maximum 700 W, idle state 45 W, Auto Power Save 2 W, standby 2 W
heat dissipation	max. 120 W, 410 BTU/h, 104 kcal/h
temperature range	0 – 40°C
cooling	temperature-controlled fan
output power	2 × 1200 W / 4 ohms, 2 × 600 W / 8 ohms (1 kHz, THD+N
minimum impedance	4 ohms
input channels	4

Controller	
digital signal processors	1
independent limiters	20
FIR filter	yes
input gain	-80 dB – +12 dB
routing gain	-80 dB – +12 dB
output gain	-80 dB – +12 dB
EQ	8 × 10 fully parametric filters, gain +/-12 dB, frequency 10 Hz – 20 kHz, Q 0.1 – 100
selective 3-band limiting	bass / mid / high
limiter / compressor	8
noise gate	8
delay	4 × 0 – 145 ms (0 – 50 m) outputs, 4 × 0 – 30 ms (0 – 10 m) inputs
X-over	8 × Linkwitz/Riley 4th order, 24dB/oktave, highpass 10 Hz – 20 kHz, lowpass 10 Hz – 20 kHz
user presets	100
speaker presets	100
system latency	1.2 ms
band-specific time constants	yes
filter technology	80-bit double precision
input	AES/EBU 32 kHz – 96 kHz, 16/24 bit
input DSP processing	yes

Remote control and remote monitoring	
remote control	Fohhn Net over RS-485, Fohhn Audio Soft, USB-C
remote monitoring	temperature, protect, signals, power supply, Fohhn Net, Fohhn Audio Soft
switching contact	load preset, standby on / off

Display (front)	
ready LED	blue = power on, blue flashing = sign
protect LED	red = error / protect / standby
USB Config LED	blue = host, remote control over USB

Connections and controls	
mains connection	1 × C14 IEC socket
switching contact 1 and 2	1 × Phoenix 3-pin
Airea Net	1 × RJ-45
outputs	1 × Phoenix 4-pin, max. 3.3 mm ² flexibel, 3.3 mm ² rigid
USB Config	1 × USB-C socket

Display (rear)

receive / send LED	remote control, Fohhn Net
--------------------	---------------------------

Input interface analog

inputs	4 × analog
signal inputs	analog, max. signal +18 dBu, phantompower (24 V DC) switchable
THD	
S/N ratio	> 108 dB/A
latency	1.0 ms
frequency response	20 Hz – 20 kHz
input impedance	10 kOhms

peso: peso neto sin equipamiento opcional
disipación de calor: ruido rosa, 6 dB de cresta, 1/4 Pmax

Interfaz de entrada Dante (DAN)



Input interface Dante (DAN)	
inputs	1 × RJ-45 100BASE-T Ethernet, Dante, 4 × 48 kHz
latency	Dante + 0.6 ms
support for AES67	yes

Fohhn Audio AG
Großer Forst 15
72622 Nuertingen
Alemania

Teléfono +49 7022 93323-0
Fax +49 7022 93324-0
www.fohhn.com
info@fohhn.com

