

Converters

ABX-5

Dante to Fohhn Aireal / AES/EBU breakout box, inputs: Dante;
outputs: Fohhn Aireal, AES/EBU, Fohhn Net



Converters ABX-5

The ABX-5 has Dante inputs and converts them to Fohhn Airea signals or AES/EBU. This means that several speakers can be operated with a single Dante card.



Main features

- Input: Dante (2 × RJ-45, primary and secondary input for redundant applications)
- Integrated Dante Brooklyn II module
- 1000Base-T Ethernet connection
- Outputs: Fohhn Airea (RJ-45), AES / EBU (XLR), Fohhn Net (RJ-45)
- Fohhn Net control signals are tunneled through Dante
- Power supply-free operation with Fohhn Airea

Available with the following color options



Black



Equipped with the following Fohhn technologies



Fohhn Airea

Possible input interfaces for this product

AIREA

Dante

Technical data

Physical features	
dimensions (w × h × d)	105 × 45 × 70 mm
Electronic features	
audio inputs	Dante Primary / Secondary
audio outputs	AES/EBU 24 Bit / 48 kHz, Airea-Net
support for AES67	Yes
power supply	wall wart 12 V – 48 V DC / 5 W, AIREA-NET 48 V
power consumption	4 W, Airea-Net Load max. 5 W
Connections	
Fohhn Net	1 × RJ-45
DC input	DC input for wall wart power supply
Dante input	2 × RJ-45 (1000Base-T Ethernet Port)
AES/EBU output	1 × XLR male
Airea	1 × RJ-45 out
Display LEDs	
power LED	green = on (front and back)
send LED	FOHHN-NET send = yellow
receive LED	FOHHN-NET receive = green

Fohhn Audio AG
Großer Forst 15
72622 Nuertingen
Germany

Phone +49 7022 93323-0
Fax +49 7022 93324-0
www.fohhn.com
info@fohhn.com

